

TWO-260/Dx-1G semi-isolated wall outlet



- Dual output isolators TV and Data
- 5 1006 MHz
- Modem Safe[™] surge protection and intermodulation reduction solution
- Meets EN Class A screening requirements
- High isolation between ports
- Diplexers for low upstream attenuation
- Easy to install
- Loop and non-loop through versions available



Overview

Designed for easy in-home installation, the TWO series contains wall outlets to suit a range of home network configurations.

The TWO-260/Dx-1G is used to connect a cable modem and a TV set to the cable network. High isolation between output ports is achieved by using high quality diplex filters and prevents the cable modem from generating interference on the TV channels.

Low upstream attenuation on the cable port provides cable operators with greater flexibility in the return path.

The TWO-260/Dx-1G's durable zinc die-cast housing with high quality in and output connectors offers trouble-free multimedia connectivity.

The different connectors for TV (IEC male) and the data port (F-female) clearly mark the dedicated connection points for TV and data applications.

The TWO-260/D4-1G has a loop through feature for cascaded in home networks.

Modem Safe

Modem Safe is a highly effective surge protection solution for sensitive network and in-home CPE. Based on passive circuits, the technology does not rely on discharge tubes, extending the lifespan of the solution.

- Blocks high and low voltage pulses and unwanted DC voltages
- Prevents internal ferrites within the product from becoming magnetised (avoiding deterioration in the performance of CPE)
- · Drives fewer reported faults
- Improves customer service
- Reduces truck rolls



TWO-260/Dx-1G semi-isolated wall outlet

Specifications

		MHz	TW0-26	TW0-260/D-1G TW0-260/D4		0/D4-1G	
Insertion loss (dB)			Тур	Max	Тур	Max	
	In -> Out	5 - 1006	N/A	N/A	4.0	4.5	
	In - > Data	85 - 1006	4.2	4.8	8.5	9.0	
	Data -> In	5 - 65	0.8	1.3	4.8	5.3	
	In -> R/TV	85 - 1006	4.0	4.8	9.0	9.5	
Return loss (dB, min)	In	5 - 65	18.0		18	18.0	
		85 - 1006¹	18	3.0	18	3.0	
	Data	5 - 65	20	0.0	18	3.0	
		85 - 1006¹	18	3.0	18	3.0	
	R/TV	85 - 1006¹	18	3.0	18	3.0	
Isolation (dB, min)	Data -> Out	5 - 1006	N/A		22.0		
	R/TV -> Data	5 - 65	45	5.0		5.0	
		85 - 1006	22	2.0	22	2.0	
Screening efficiency (dB, typ) Minimum exceeds Class A ²		5 - 300	95.0		95	95.0	
Millimum exceeds class A		300 - 470	90	0.0	90	0.0	
		470 - 950	85	5.0	85	5.0	
		950 - 1006	85	5.0	85	5.0	
Intermodulation p+q (dBc, min)	No surge ³	-110.0					
	25 V surge ⁴	-110.0					
Surge Class conformance ⁵	All ports	1 kV 1.2/50μs					
Connectors	In	Terminal Block					
	Data	F-female					
	R/TV	IEC-male					
Material	Housing	Nickel plated zinc die-cast					
	Fooring	Back cover tin plated steel sheet					
Immediance (Ohm tun)	F-spring	Silver plated phosphor bronze					
Impedance (0hm, typ)		75					
Dimensions (mm)	LxHxD	70.2x70.2x30.0					
Equipment Approval	CE						

Remarks

1	Where frequency is above 40 MHz, deduct 1.5 dB/Octave (with a minimum of 10 dB) $$
2	Tested according to EN 50083-2 2006
3	Two carriers (50 & 55MHz),out to in, @ 120dBµV, after 10 pulses (25V/1,2µS rise time/500µS duration) at all ports
4	Two carriers (50 & 55MHz), out to in, @ 120dBµV, after 1 pulse 1KV (1,2 μ S risetime/50 μ S fall time) at Input.
5	Tested according to IEC 61000-4-5 2005
	Measurements taken at room temperature
	DC power blocking on all F ports

Ordering information

	Item Name	Article number			
	TW0-260/D-1G	19003908			
TW0-260/D4-1		19003909			

© Copyright 2012 Technetix Group Limited. All rights reserved.

This document is for information only. Features and specifications are subject to change without notice. Technetix, the Technetix logo, Ingress Safe, Modern Safe and certain other marks and logos are trade marks or registered trade marks of Technetix Group Limited in the UK and certain other countries. Other brand and company names are trade marks of their respective owners. Technetix protects its technology and designs by registering patents, trade marks and designs in Europe and certain other countries.